



Please follow the script as provided. If you still experience problems go to www.emedny.org/POS and locate the online presentations to view or call the eMedNY Provider Services Call Center at (800) 343-9000.

For use with only NYS Medicaid VeriFone Vx610

Vx610 Cellular Download

1. Press the **RED** key (terminal should display DATE, and TIME).
2. Press the **F2** key. (terminal should display VCS CDMA).
3. Press the **Review** key to enter the CommServer CDMA Configuration Menu.
4. Press the **Setup** key. The terminal should display DOWNLOAD SETUP ROAMING MAINTENANCE.
5. Press the **F1** key (DOWNLOAD). The terminal should display VCS Download Group ID.
6. Enter "2" for the group ID and then Press the **Green** key. The terminal should display VCS Download F1 FULL F2 PARTIAL.
7. Press the **F2** key for Partial Download. The terminal should display VCS Download F1 TCPIP F2 SSL.
8. Press the **F1** key for TCPIP. The terminal should display VCS Download main screen F3 Edit F4 Start.
9. Press the **F3** key to Edit. The terminal should display VCS Download *ZP Host IPAddr:Port.
10. Use the **YELLOW** key to fully delete the information under *ZPHost IPAddr:Port.
11. Type the following (excluding comas): **1,9,2,1, Alpha, Alpha, Alpha, 3,0,1, Alpha, Alpha, Alpha,1,0,0,1,Alpha,Alpha,Alpha,5,2,#,Alpha,Alpha,8,0,1,3.**
*The screen should now display the following under *ZPHost IPAddr:Port:
192.30.100.52:8013; press the **Green** key.*
12. The terminal will display the *ZA Application ID. **Press the Green key.**
13. The terminal will display *ZT Terminal ID. **Press the Green key.**
14. The device will return to the VCS Download main screen. Press the **F4** key to START the download.

The Device will then perform the following:

- Test and Restart
- Initialize CommServer
- Download with Status Indicator.

The download will complete and return to the VMAC Main Menu.

*If device does not respond or fails, an error message will print. The terminal should display **RETRY DOWNLOAD? YES F3 NO F4**

****If the device does not respond, press the RED key and repeat process again.**